



Model #164W RTM kit - P/N E225-0164-24-92

Parts list :

- 1 ea. Full PCB assy. ref# E225-0131-01-67
- 1 ea. Option PCB assy. ref# E225-0134-01-76
- 1 ea. Supercap 0.22F/5V5 ref# E225-0140-01-94
- 1 ea. Power male conn. ref# E225-0141-02-01
- 1 ea. Power female conn. ref# E225-0141-03-02
- 2 ea. Rewired front warm white PLCC leds ref# E225-01XX-XX-XX
- 1 ea. Rewired dual // rear super red PLCC leds ref# E225-0143-04-09
- 2 ea. Rewired exhaust yellow 0603 Led ref# E225-144-01-09

Rmk : Leds (but 2nd exhaust) & power male conn. already soldered.

Model #164W

Features :

- * Reverse voltage & overcurrent protection
- * Stabilized power head & tail lights (w. energy backup).
- * High intensity brake lights.
- * Exhaust flame simulation.
- * On idle after 2 seconds, "dancing" headlights AND flashing taillights.

Main characteristics :

Dimensions (L x l x h) : 29 x 10 x 6 mm max (w. one supercap)
 Weight : 3.27 gr (w. power conn & one supercaps)
 Power supply : min 8Vdc/ac - Max 25Vdc/ac (Davic compatible)
 Power consumption : Max 75mA peak - 15mA continuous (@12.8Vdc)
 Lighting backup : > 1 minute

!!! CAUTION !!! SuperCap is polarized !!!

All square pads may be used as negative common (0 volt)

Alternative or second exhaust flame led connections

#164W

rev. 06/02/2011



<http://www.zmachine.be> - phl@zmachine.be - Zmachine Electric Motorsport